

Features

- 2-channel isolated barrier
- 24 V DC supply (Power Rail)
- Thermocouple, RTD, potentiometer or voltage input
- Voltage output 0/1 V ... 5 V
- Configurable by **PACTware**
- Line fault (LFD) and sensor burnout detection
- Up to SIL 2 acc. to IEC 61508/IEC 61511

Function

This isolated barrier is used for intrinsic safety applications. It is designed to connect RTDs, thermocouples, or potentiometers in the hazardous area, and provide a proportional 0/1 V ... 5 V signal to the safe area.

The barrier offers 3-port isolation between input, output, and power supply.

A removable terminal block K-CJC-** is available for thermocouples when internal cold junction compensation is desired.


A fault is indicated by a red flashing LED per NAMUR NE44 and user-configured fault outputs.

The unit is easily programmed with the **PACTware™** configuration software.

A collective error messaging feature is available when used with the Power Rail system.


For additional information, refer to the manual and www.pepperl-fuchs.com.

Assembly



SIL2

Connection



General specifications	
Signal type	Analog input
Supply	
Connection	terminals 14+, 15- or power feed module/Power Rail
Rated voltage U_r	20 ... 30 V DC
Ripple	within the supply tolerance
Power dissipation/power consumption	$\leq 0.8 \text{ W} / 0.8 \text{ W}$
Input	
Connection	terminals 1, 2, 3; 4, 5, 6
RTD	type Pt10, Pt50, Pt100, Pt500, Pt1000 (EN 60751: 1995) type Pt10GOST, Pt50GOST, Pt100GOST, Pt500GOST, Pt1000GOST (6651-94) type Cu10, Cu50, Cu100 (P50353-92) type Ni100 (DIN 43760)
Measuring current	approx. 200 μA with RTD
Types of measuring	2-, 3-wire connection
Lead resistance	$\leq 50 \Omega$ per line
Measuring circuit monitoring	sensor breakage, sensor short-circuit
Thermocouples	type B, E, J, K, N, R, S, T (IEC 584-1: 1995) type L (DIN 43710: 1985) type TXK, TXKH, TXA (P8.585-2001)
Cold junction compensation	external and internal
Measuring circuit monitoring	sensor breakage
Potentiometer	0 ... 20 k Ω (2-wire connection), 0.8 ... 20 k Ω (3-wire connection)
Voltage	selectable within the range -100 ... 100 mV
Input resistance	$\geq 1 \text{ M}\Omega$ (-100 ... 100 mV)
Output	
Voltage output	0 ... 5 V or 1 ... 5 V ; output resistance: $\leq 5 \Omega$; load: $\geq 10 \text{ k}\Omega$
Connection	output I: terminals 7-, 8+ output II: terminals 10-, 11+
Fault signal	downscale 0 V or 0.5 V, upscale 5.375 V
Transfer characteristics	
Deviation	
After calibration	<u>Pt100</u> : $\pm (0.06 \text{ \% of measurement value in K} + 0.1 \text{ K (4-wire connection)})$ <u>thermocouple</u> : $\pm (0.05 \text{ \% of measurement value in } ^\circ\text{C} + 1 \text{ K (1.2 K for types R and S)})$ this includes $\pm 0.8 \text{ K}$ error of the cold junction compensation <u>mV</u> : $\pm 50 \mu\text{V}$ <u>potentiometer</u> : $\pm 0.05 \text{ \% of full scale, (excludes errors due to lead resistance)}$ <u>output</u> : 1 to 5 V output: $\pm 4 \text{ mV}$ from 0 to 103.1 % of span; 0 to 5 V output: $\pm 4 \text{ mV}$ from 0.3 to 102.5 % of span
Influence of ambient temperature	deviation of CJC included: <u>Pt100</u> : $\pm (0.0015 \text{ \% of measurement value in K} + 0.0075 \text{ \% of span})/\text{K } \Delta T_{\text{amb}}^{*)}$ <u>thermocouple</u> : $\pm (0.02 \text{ K} + 0.005 \text{ \% of measurement value in } ^\circ\text{C} + 0.0075 \text{ \% of span})/\text{K } \Delta T_{\text{amb}}^{*)}$ <u>mV</u> : $\pm (0.01 \text{ \% of measurement value} + 0.0075 \text{ \% of span})/\text{K } \Delta T_{\text{amb}}^{*)}$ <u>potentiometer</u> : $\pm 0.0075 \text{ \% of span}/\text{K } \Delta T_{\text{amb}}^{*)}$ $^{*)} \Delta T_{\text{amb}}$ = ambient temperature change referenced to 23 °C (296 K)
Influence of supply voltage	$< 0.01 \text{ \% of span}$
Reaction time	worst case value (sensor breakage and/or sensor short circuit detection enabled) mV: 1.2 s, thermocouples with CJC: 1.4 s, thermocouples with fixed ref. temp: 1.4 s, 3- or 4-wire RTD: 1.1 s, 2-wire RTD: 920 ms, Potentiometer: 3-wire connection 2.8 s, 2-wire connection 2.25 s
Galvanic isolation	
Output/supply, programming input	functional insulation, rated insulation voltage 50 V AC There is no electrical isolation between the programming input and the supply. The programming cable provides galvanic isolation so that ground loops are avoided.
Directive conformity	
Electromagnetic compatibility	
Directive 2014/30/EU	EN 61326-1:2013 (industrial locations)
Conformity	
Electromagnetic compatibility	NE 21:2006
Degree of protection	IEC 60529:2001
Protection against electrical shock	UL 61010-1:2004
Ambient conditions	
Ambient temperature	-20 ... 60 °C (-4 ... 140 °F)
Mechanical specifications	
Degree of protection	IP20
Mass	approx. 130 g
Dimensions	20 x 119 x 115 mm (0.8 x 4.7 x 4.5 inch) , housing type B2
Mounting	on 35 mm DIN mounting rail acc. to EN 60715:2001
Data for application in connection with hazardous areas	

EU-Type Examination Certificate		CESI 04 ATEX 143
Marking		<div>Ex</div> II (1)G [Ex ia Ga] IIC <div>Ex</div> II (1)D [Ex ia Da] IIIC <div>Ex</div> I (M1) [Ex ia Ma] I
Input		Ex ia
Inputs		terminals 1, 2, 3, 4, 5, 6 (for passive equipment)
Voltage	U_o	9 V
Current	I_o	22 mA
Power	P_o	50 mW
Analog outputs, power supply, collective error		
Maximum safe voltage	U_m	250 V (Attention! This is not the rated voltage.)
Interface		
Maximum safe voltage	U_m	250 V (Attention! The rated voltage is lower.), RS 232
Certificate		TÜV 02 ATEX 1797 X
Marking		<div>Ex</div> II 3G Ex nA II T4
Galvanic isolation		
Input/Other circuits		safe electrical isolation acc. to IEC/EN 60079-11, voltage peak value 375 V
Directive conformity		
Directive 2014/34/EU		EN 60079-0:2012+A11:2013 , EN 60079-11:2012 , EN 60079-15:2010 , EN 50303:2000
International approvals		
UL approval		
Control drawing		116-0316
CSA approval		
Control drawing		366-024CS-12 (cCSAus)
IECEX approval		
IECEX certificate		IECEX TUN 07.0003 IECEX CML 16.0126X
IECEX marking		[Ex ia Ga] IIC [Ex ia Da] IIIC [Ex ia Ma] I Ex nA IIC T4 Gc
General information		
Supplementary information		Observe the certificates, declarations of conformity, instruction manuals, and manuals where applicable. For information see www.pepperl-fuchs.com .

Accessories

Power feed module KFD2-EB2

The power feed module is used to supply the devices with 24 V DC via the Power Rail. The fuse-protected power feed module can supply up to 150 individual devices depending on the power consumption of the devices. A galvanically isolated mechanical contact uses the Power Rail to transmit collective error messages.

Power Rail UPR-03

The Power Rail UPR-03 is a complete unit consisting of the electrical inset and an aluminium profile rail 35 mm x 15 mm. To make electrical contact, the devices are simply engaged.

Profile Rail K-DUCT with Power Rail

The profile rail K-DUCT is an aluminum profile rail with Power Rail insert and two integral cable ducts for system and field cables. Due to this assembly no additional cable guides are necessary.



Power Rail and Profile Rail must not be fed via the device terminals of the individual devices!

K-CJC-**

This removable terminal block with integrated temperature measurement sensor is needed for internal cold junction compensation for thermocouples. One K-CJC-** is needed for each channel.

PACTware™

Device-specific drivers (DTM)

Adapter K-ADP-USB

Programming adapter for parameterisation via the serial USB interface of a PC/Notebook