

<b>Brand</b>	UNI-T
<b>Model</b>	UT136C
<b>Quantity</b>	1
<b>Color</b>	Red + dark grey
<b>Material</b>	ABS plastic housing
<b>LCD Display</b>	2"
<b>Features</b>	Automatic measurement
<b>Application</b>	Measuring voltages & currents
<b>Max. Display</b>	3999
<b>DC Voltage</b>	400mV/4V/40V/400V/500V +/- (0.8%+1)
<b>AC Voltage</b>	400mV/4V/40V/400V/500V +/- (1.2%+3)
<b>DC Current</b>	400uA/4mA/40mA/400mA/4A/10A +/- (1
<b>AC Current</b>	400uA/4mA/40mA/400mA/4A/10A +/- (1.2%+5)
<b>Resistance</b>	400ohm/4000ohm/40Kohm/400Kohm/4Mohm/40Mohm +/- (1.0%+2) ohm
<b>Frequency</b>	10Hz/100Hz/1KHz/10KHz/100KHz/1MHz/10MHz +/- (0.5%+3)
<b>Other Data</b>	Temperature: -40'C~1000'C +/- (2.5%+3); Duty cycle: 0.1%~99.9%; Other features: Diode test / Continuity buzzer / Auto power off / Low voltage alarm & Data retention; Voltage measurement input impedance: >=10Mohm
<b>Power Supply</b>	Powered by 1 x 9V battery (included)
<b>Packing List</b>	1 x Digital multimeter 2 x Test leads (90cm) 1 x 9V battery 1 x Temperature probe (97cm)

