

**Main Features**

- Power is 9V battery (6F22)
- LCD size is 49\*18mm
- Product colour is red and grey

**Specifications**

Specification	UT136D	
Basic Function	Range	Accuracy
DC voltage	400mV/4V/40V/400V/500V	±(0.8%+1)
AC voltage	400mV/4V/40V/400V/500V	±(1.2%+3)
DC current	400uA/4mA/40mA/400mA/4A/10A	±(1.0%+2)
AC Current	400uA/4mA/40mA/400mA/4A/10A	±(1.2%+5)
Resistance	400Ω/4000Ω/40kΩ/400kΩ/4MΩ/40MΩ	±(1.0%+2)
Temperature	-40°C~1000°C	
Frequency	10Hz/100Hz/1kHz/10kHz/100kHz/1MHz/10MHz	±(0.5%+3)
Duty Cycle	0.1%~99.9%	√
Special Function		
Diode Testing	√	
Continue Buzzer	√	
NCV	√	
Auto Off	√	
Low Battery. Display	√	
Input Imp. For DC Voltage Measure	≥10MΩ	√
Auto Data Hold	√	
Max. Display	3999	

**Package Including**

- 1 x UT136D Auto Range Multimeter AC DC Frequency Resistance
- 1 x Original Package